

**B.E.G.****LUXOMAT®**

## RC-plus next N 130 Set 93324-92467-97005

230V PIR outdoor motion detector with a 130° detection angle and a range of up to 20 m (450 m<sup>2</sup>), featuring anti-crawl protection and remote control capability

### Order data

| Designation                       | Colour | Art.No |
|-----------------------------------|--------|--------|
| RC-plus next N 130                | brown  | 93324  |
| Wire basket BSK (Ø 164 x 143 mm)  | white  | 92467  |
| Inside corner socket RC-plus next | white  | 97005  |

### Areas of application

- outdoor areas (entrances/access roads)
- parking areas
- underground car parks
- high-bay warehouse

## Technical data

|  |  |
|--|--|
| Voltage:                               | 110 - 240 V AC<br>50 / 60 Hz (can also be supplied with other operating voltages ON request) |
| Dimensions:                            | <b>Ø 164 x 143 mm (92467) + 60 x 61 x 68 mm (97005)</b>                                      |
| Power consumption:                     | approx. 0.5 W  |
| Detection area:                        | horizontal 130° (Wall mounting)<br>max. 20 m across<br>max. 6 m towards                      |
| Range:                                 | max. 4 m creep protection  |
| Monitored area (tangential movement):  | 450 m <sup>2</sup> / 2.5 m mounting height   |
| Mounting height min./max./recommended: | 2 m / 5 m / 2.5 m  |
| Degree / class of protection:          | IP54 / Class II  |
| Impact strength:                       | <b>IK09 (92467)</b>  |
| Ambient temperature:                   | -25 °C to +50 °C   |
| Housing:                               | <b>polycarbonate, UV-resistant + coated steel basket (92467)</b>                             |
| Material color:                        | brown mat, similar to RAL8014  |

### Channel 1 (lighting control)

|                      |  |
|----------------------|--|
| Switching power:     | 3000 W, $\cos \varphi = 1$<br>1500 VA, $\cos \varphi = 0.5$<br>800 W LED<br>max. inrush current $I_p$ (20 ms) = 165 A<br>max. inrush current $I_p$ (200 $\mu$ s) = 800 A |
| Type of contact (k): | 1x $\mu$ -contact, NO contact with tungsten pre-make contact   |
| Follow-up time:      | 15 sec - 16 min, Pulse   |
| Switch-on threshold: | 2 - 500 Lux  |

## Product information

Set : RC-plus next N 130 + Wire basket BSK (Ø 164 x 143 mm) white + Inside corner socket RC-plus next white mat, similar to RAL9010

Motion detector with 130° detection area and creep protection

Mechanical range adjustment

Different follow-up time depending on direction of movement

Uninterrupted parallel circuit detection of several detectors

Manual switching via push-button possible

Adjustable ball head

Immediate operation using factory settings

Additional functions can be set up using the optional remote control.

Zero crossing switching

Socket compatible to RC-plus (next) and Vario

Faulty switching due to animals can be avoided by reducing the sensitivity

Easy mounting thanks to plug base

Wall, ceiling and corner mounting

Factory settings 3 min and 20 lux



## Set items

To receive the bundle according to the technical specification, please order the items listed.



### RC-plus next N 130

Art.No: 93324

Voltage: 110 – 240 V AC 50 / 60 Hz (can also be supplied with other operating voltages ON request)

Dimensions: 121 x 71 x 85 mm

Power consumption: approx. 0.5 W



### Wire basket BSK (Ø 164 x 143 mm)

Art.No: 92467

Dimensions: Ø 164 x 143 mm

Impact strength: IK09

Housing: coated steel basket



### Inside corner socket RC-plus next

Art.No: 97005

Dimensions: 60 x 61 x 68 mm

Degree / class of protection: IP54

Housing: Housing UV- and shockresistant