

# B.E.G. LUXOMAT<sup>®</sup> net



## PD2N-RF-KNXs-DX-FC Set 93580-93761

KNX RF PIR Motion Sensor (Deluxe) with 360° detection and a range of up to Ø10m (78 m<sup>2</sup>), communication via KNX RF wireless

### Order data

Designation	Colour	Art.No
PD2N-RF-KNXs-DX-FC	white	93580
Cover ring PD2N FM	anthracite	93761

## Technical data

Voltage:	230 V AC $\pm 10\%$ 50 / 60 Hz
Dimensions:	Ø 83 x 81 mm
Power consumption:	1 W
Detection area:	horizontal 360° (Ceiling mounting) max. Ø 10 m across max. Ø 6 m towards max. Ø 4 m seated
Range:	78 m <sup>2</sup> / 2.5 m mounting height
Monitored area (tangential movement):	2 m / 5 m / 2.5 m
Mounting height min./max./recommended:	IP20 / Class II
Degree / class of protection:	IK05
Impact strength:	-5 °C to +45 °C
Temperature measurement range:	-25 °C to +55 °C
Ambient temperature:	polycarbonate, UV-resistant
Housing:	<b>anthracite mat, similar to RAL7016 (93761)</b>
Material color:	2
Number of light sensors:	1
Number of PIR sensors:	Yes
KNX RF 256:	Yes
KNX Secure:	2300 W, $\cos \varphi$ = 1 1150 VA, $\cos \varphi$ = 0.5 300 W LED
Switching power:	µ-contact, dry NO contact
Type of contact (k):	5 - 100 % / OFF / 1 min - 255 min
Orientation light:	5 - 100 %
Night light:	Brightness set value: 5 - 2000 Lux
Brightness set value:	868.3 MHz (EU), RF1.R, 10 dBm
Frequency:	max. 150 m
Transmit range:	

## Product information

Set : PD2N-RF-KNXs-DX-FC + Cover ring PD2N FM anthracite mat, similar to RAL7016

KNX RF occupancy detector

Communication via KNX RF radio

KNX Secure ready

HCL/RGB control

Parameterisation from ETS 5 for integration into KNX systems

Individual adaption of the PIR sensor sensitivity

Mixed light measurement using internal, external and remote (optional) light sensors

Intelligent semi-automatic mode, occupancy-independent regulating mode (photoelectric switch), full automatic mode

1 x light output (for regulating or switching), 1 x slave output, 3 x HVAC outputs (separately programmable)

Regulation of up to three lighting groups using offset (external influence possible)

Short presence, self-adjusting follow-up time, corridor function

Various locking functions

Soft-start

Two logic modules

Recall of light scenes

Deactivatable status indicators

Temperature- and noise sensor

Detection area can be extended thanks to master-slave-mode

Extensive optimization options for light measurement

Measured light value is communicated to the bus

Adaption of dimming curve

Bidirectionally remote control-capable with the IR adapter and the B.E.G. smartphone app

PIN code

IR remote control-capable via IR remote control (optionally)

5 button remote control, programmable at choice (accessory)

Programming button (phys. address) can be operated via remote control

HVAC mode (0=automatic, 1=comfort, 2=stand-by, 3=economy, 4=antifreeze/heat protection)

Manual influence via external KNX push buttons possible

Function control (heartbeat, cyclical sending)

Occupancy simulation

Forced switch-off

Intelligent central-off function

Premonition of switch-off

Burn-in function for fluorescent lamps selectable from 1h till 100h

Behaviour upon bus voltage return definable at choice

Variable safety pause after switching off the lights

Optional potential-free switching contact for switching operation

Repeater function can be activated

Perfectly suited for renovations and modernisations

Due to its radio frequency of 868 MHz, the device is only approved for use in Europe (+United Arab Emirates)




## Set items

To receive the bundle according to the technical specification, please order the items listed.



**PD2N-RF-KNXs-DX-FC**  
Art.No: 93580

Voltage: 230 V AC  $\pm 10\%$  50 / 60 Hz  
Dimensions:  $\varnothing$  83 x 81 mm  
Power consumption: 1 W



**Cover ring PD2N FM**  
Art.No: 93761

Dimensions:  $\varnothing$  106 x 20 mm  
Impact strength: IK05  
Housing: polycarbonate, UV-resistant