

B.E.G. LUXOMAT[®] net



PD2N-RF-KNXs-DX-FC Set 93580-93773

- Voltage: 230 V AC \pm 10% 50 / 60 Hz
- Dimensions: \varnothing 83 x 81 mm
- Power consumption: 1 W

Order data

Designation	Colour	Art.No
PD2N-RF-KNXs-DX-FC	white	93580
Cover ring PD2N FC	black	93773

Technical data

Voltage:	230 V AC \pm 10% 50 / 60 Hz
Dimensions:	Ø 83 x 81 mm
Power consumption:	1 W
Detection area:	horizontal 360° (Ceiling mounting) max. Ø 10 m across max. Ø 6 m towards max. Ø 4 m seated
Range:	78 m ² / 2.5 m mounting height
Monitored area (tangential movement):	2 m / 5 m / 2.5 m
Mounting height min./max./recommended:	IP20 / Class II
Degree / class of protection:	IK05
Impact strength:	-5 °C to +45 °C
Temperature measurement range:	-25 °C to +55 °C
Ambient temperature:	polycarbonate, UV-resistant
Housing:	black mat, similar to RAL9005 (93773)
Material color:	2
Number of light sensors:	1
Number of PIR sensors:	Yes
KNX RF 256:	Yes
KNX Secure:	2300 W, $\cos \varphi$ = 1 1150 VA, $\cos \varphi$ = 0.5 300 W LED
Switching power:	μ -contact, dry NO contact
Type of contact (k):	5 - 100 % / OFF / 1 min - 255 min
Orientation light:	5 - 100 %
Night light:	Brightness set value: 5 - 2000 Lux
Brightness set value:	868.3 MHz (EU), RF1.R, 10 dBm
Frequency:	max. 150 m
Transmit range:	

Product information

Set : PD2N-RF-KNXs-DX-FC + Cover ring PD2N FC
black mat, similar to RAL9005

KNX RF occupancy detector

Communication via KNX RF radio

KNX Secure ready

HCL/RGB control

Parameterisation from ETS 5 for integration into KNX systems

Individual adaption of the PIR sensor sensitivity

Mixed light measurement using internal, external and remote (optional) light sensors

Intelligent semi-automatic mode, occupancy-independent regulating mode (photoelectric switch), full automatic mode

1 x light output (for regulating or switching), 1 x slave output, 3 x HVAC outputs (separately programmable)

Regulation of up to three lighting groups using offset (external influence possible)

Short presence, self-adjusting follow-up time, corridor function

Various locking functions

Soft-start

Two logic modules

Recall of light scenes

Deactivatable status indicators

Temperature- and noise sensor

Detection area can be extended thanks to master-slave-mode

Extensive optimization options for light measurement

Measured light value is communicated to the bus

Adaption of dimming curve

Bidirectionally remote control-capable with the IR adapter and the B.E.G. smartphone app

PIN code

IR remote control-capable via IR remote control (optionally)

5 button remote control, programmable at choice (accessory)

Programming button (phys. address) can be operated via remote control

HVAC mode (0=automatic, 1=comfort, 2=stand-by, 3=economy, 4=antifreeze/heat protection)

Manual influence via external KNX push buttons possible

Function control (heartbeat, cyclical sending)

Occupancy simulation

Forced switch-off

Intelligent central-off function

Premonition of switch-off

Burn-in function for fluorescent lamps selectable from 1h till 100h

Behaviour upon bus voltage return definable at choice

Variable safety pause after switching off the lights

Optional potential-free switching contact for switching operation

Repeater function can be activated

Perfectly suited for renovations and modernisations

Due to its radio frequency of 868 MHz, the device is only approved for use in Europe (+United Arab Emirates)



Set items

To receive the bundle according to the technical specification, please order the items listed.



PD2N-RF-KNXs-DX-FC
Art.No: 93580

Voltage: 230 V AC $\pm 10\%$ 50 / 60 Hz
Dimensions: $\varnothing 83 \times 81$ mm
Power consumption: 1 W



Cover ring PD2N FC
Art.No: 93773

Dimensions: $\varnothing 82 \times 13$ mm
Impact strength: IK05
Housing: polycarbonate, UV-resistant