



PD2N-KNXs-ST-FM Set 93511-93763

- Voltage: via KNX BUS
- Dimensions: Ø 106 x 42 mm
- Typ. power input: 12 mA

Order data

| Designation | Colour | Art.No |
|--------------------|--------|--------|
| PD2N-KNXs-ST-FM | white | 93511 |
| Cover ring PD2N FM | black | 93763 |

Technical data

| | |
|--|--|
| Voltage: | via KNX BUS |
| Dimensions: | Ø 106 x 42 mm |
| Typ. power input: | 12 mA |
| Detection area: | horizontal 360° (Ceiling mounting) max. Ø 10 m across max. Ø 6 m towards max. Ø 4 m seated |
| Range: | 78 m ² / 2.5 m mounting height |
| Monitored area (tangential movement): | 2 m / 5 m / 2.5 m |
| Mounting height min./max./recommended: | IP20 / Class III |
| Degree / class of protection: | IK05 |
| Impact strength: | -25 °C to +55 °C |
| Ambient temperature: | polycarbonate, UV-resistant |
| Housing: | 2 |
| Number of light sensors: | black mat, similar to RAL9005 (93763) |
| Material color: | 1 |
| Number of PIR sensors: | Yes |
| KNX TP 256: | Yes |
| KNX Secure: | 5 – 100 % / OFF / 1 min – 255 min |
| Orientation light: | 5 – 100 % |
| Night light: | 5 – 2000 Lux |
| Brightness set value: | |

Product information

Set : PD2N-KNXs-ST-FM + Cover ring PD2N FM black mat, similar to RAL9005

KNX occupancy detector with integrated KNX bus connector

KNX Secure ready

Parameterisation from ETS 5 for integration into KNX systems

Individual adaption of the PIR sensor sensitivity

Mixed light measurement using internal, external and remote (optional) light sensors

Intelligent semi-automatic mode, occupancy-independent regulating mode (photoelectric switch), full automatic mode

1 x Light (for regulating or switching), 1 x slave output, 3 separate HVAC-blocs

Regulation of up to three lighting groups using offset (external influence possible)

Short presence, self-adjusting follow-up time, corridor function

Various locking functions

Soft-start

Recall of light scenes

Deactivatable status indicators

The product database for import into the ETS database can be downloaded from the B.E.G. homepage.

Detection area can be extended thanks to master-slave-mode

Extensive optimization options for light measurement

Measured light value is communicated to the bus

Adaption of dimming curve

Bidirectionally remote control-capable with the IR adapter and the B.E.G. smartphone app

PIN code

IR remote control-capable via IR remote control (optionally)

Programming button (phys. address) can be operated via remote control

HVAC mode (0=automatic, 1=comfort, 2=stand-by, 3=economy, 4=antifreeze/heat protection)

Manual influence via external KNX push buttons possible

Function control (heartbeat, cyclical sending)

Forced switch-off




Intelligent central-off function

Premonition of switch-off

Burn-in function for fluorescent lamps selectable from 1h till 100h

Behaviour upon bus voltage return definable at choice

Variable safety pause after switching off the lights



Set items

To receive the bundle according to the technical specification, please order the items listed.



PD2N-KNXs-ST-FM

Art.No: 93511

Voltage: via KNX BUS
Dimensions: Ø 106 x 42 mm
Typ. power input: 12 mA



Cover ring PD2N FM

Art.No: 93763

Dimensions: Ø 106 x 20 mm
Impact strength: IK05
Housing: polycarbonate, UV-resistant