

**B.E.G.****LUXOMAT<sup>®</sup>net**

## PBM-DALI-LINK-4W-BLE

Prod.No. 92732 EAN: 4007529927326

Parameterisation of the DALI-LINK solution via Bluetooth with a smartphone and the B.E.G. DALI-LINK App.

4 inputs for conventional push buttons, freely configurable

Operating modes: Standard, staircase or scene mode

### Order data

| Designation          | Colour | Art.No |
|----------------------|--------|--------|
| PBM-DALI-LINK-4W-BLE | -      | 92732  |

## Technical data

|                                  |  |
|----------------------------------|--|
| Voltage:                         | via DALI Bus, max.<br>22.5 V DC                      |
| Dimensions:                      | 38 x 38 x 14 mm                                      |
| Settings:                        | Smartphone with DALI-<br>LINK App (iOS /<br>Android) |
| Typ. power input:                | 7 mA   |
| Degree / class of<br>protection: | IP20 / Class II                                      |
| Ambient<br>temperature:          | -25 °C to +50 °C                                     |
| Housing:                         | Polycarbonate  |
| Material color:                  | -  |
| Cable length:                    | max. 50 cm   |
| Follow-up time:                  | 1 min - 150 min<br>(staircase mode only)             |
| Frequency:                       | 2.4 GHz ISM band,<br>GFSK 3 dBm                      |

## Product information

DALI pushbutton module with 4 binary inputs and integrated Bluetooth gateway for hidden mounting behind flush mount switches.

Parameterisation of the DALI-LINK solution via Bluetooth with a smartphone and the B.E.G. DALI-LINK App.

4 inputs for conventional push buttons, freely configurable

Operating modes: Standard, staircase or scene mode

Integrated buzzer to determine location of installed device

Full range of functions can only be activated with other products of the product group B.E.G. LUXOMAT®net DALI-LINK

Android -

<https://play.google.com/store/apps/details?id=com.elpla.begbl>

iOS -

<https://itunes.apple.com/de/app/b-e-g-luxomatnet-dali-link/id1342462121>

This article is a component of a lighting control system from B.E.G., which supports the use of DALI control gear (luminaires, relays) from other manufacturers

The use of DALI application controllers from other manufacturers is not supported

The use of DALI input devices (sensors, push-buttons) from other manufacturers is not supported

Additional system components (hardware) from B.E.G. are required

Additional free software from B.E.G. is required

Suitable for: 93840, 93845, ...



